

Owner Retrieval

13:37:34	***** P R E D I C T 4.3.1 *****	2003-05-31
Plan 4	- (OW) Owner Retrieval -	Profile HNO
Retrieval Type		
D Owners		
O Owners with no user		
U Objects with no owners		
X Cross reference owners		
Retrieval type		
Output mode* S Select		
Owner ID		
Output options ..* Profile HNO,used		
Related type....*		
Command ==>		
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---		
Help Next Stop Last LnKEl Flip Print Impl AdmFi SelFi Prof Main		

Note:

Owners cannot be used as additional selection criteria (restrictions) when retrieving information on owners.

Owner-specific Retrieval Functions

Owners with no User - Code O

Lists owners which are not assigned to any user.

Direct command: FREE OWNER

Valid output modes: List, Select.

Objects with no Owners - Code U

Reports on objects that have no owner.

Command: EMPTY OWNER

Valid output modes: List, Select.

Note:

It is not possible to select objects for immediate processing from lists produced with the output mode Select. Objects can however be selected for later processing from the workplan.

Cross Reference Owners - Code X

Lists all objects, that have specified owners in their owner list.

Command: XREF OWNER

Valid output mode: Cross reference.

```

13:39:12          ***** P R E D I C T 4.3.1 *****          2003-05-31
                    - Cross Reference for Owner -

Owner ID ..... BOE
-----
Program ID ..... C-PR-P
Keywords
  COO
Extracts
  HEB-TEST, STK-ET-2, ARH-ET-0, BOE-ALL
Owner ID
  HEB
  ? User ID   User name
  ?   HEB-1
  ?   HEB-PUR   TEST
  GER
  ? User ID   User name
  ?                               >>> No user exists <<<
  BOE
  ? User ID   User name

Command ==>
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
                    Quit          RFind Flip  -      +          Left  Right
  
```

Layout of Owner Lists

```

13:40:07          ***** P R E D I C T 4.3.1 *****          2003-05-31
                    - List Owner -

-----
Cmd  Owner ID                               User ID   User name

  1 B                               >>> No user exists <<<
  2 BER                               BER
  3 BOE                               BOE1
                                   BOE2
  4 BOE-OW01                          BOE3
  
```

Meaning of Columns

Owner ID	ID of owner.
User ID	IDs of the persons the owner represents.
User name	Names of the persons the owner represents.
	In select lists >>> multiple <<< is displayed if an owner is assigned to more than one user.

Output Options for Owner Retrieval

Note:

Unless output mode is S, the option Cover page is always valid.

Note:

Page size is only applicable when printing or if general default parameter "Use SAG Editor for output" is set to Y.

Page size is not applicable in batch mode.

Retrieval Type	D	O	U	X
Output Mode	L	L	L	X
Current/Related	c	c	c	r
Attributes				Y
Connecting character				Y
Description				Y
Dummy/Placeholder				Y
Extract				Y
Keywords				Y
Mark implementation			Y	Y
No. abstract lines			Y	Y
Owner				Y
With users				Y
Sorted by field			Y	Y
Use Con-form				Y